

# Dynamic Engineers Inc.

Website: <a href="www.DynamicEngineers.com">www.DynamicEngineers.com</a> Email: <a href="mailto:lnguiry@DynamicEngineers.com">lnguiry@DynamicEngineers.com</a> PLL1919BQ-SS-2739MHz-2815MHz-A 2739-2815MHz SMD Phase Locked Loop (PLL) Synthesizer

#### **Features and Benefits**

Frequency Range: 2739-2815MHz

Supply Voltage: 5.0V Current: 25mA Max. 3 wire serial integer PLL Output power: +2.0dBm Max. Phase noise: -91dBc/Hz@10KHz Operating temperature: -40°C--+85°C

Size: 19.0x19.0x5.8mm Package type: SMD


## **Typical Applications**

SATCOM radio link Point-to-Point radio Receiver MMDS Test Equipment WiMAX Radar


### **Mechanical Drawing & Pin Connections**


**Drawing No:** 

MD240072-1









#### Pin Connections:

Pin	Function			
1	CLK			
2	DATA			
3	LE			
4	Ref. IN			
5-8	GND			
9	VCC(VCO)			
10-12	GND			
13	RF Out			
14	GND			
15	5 Vcp(PLL)			
16	6 Lock Detect			
7&18	GND			

Unit in mm 1mm = 0.0394 inches



# Dynamic Engineers Inc.

Website: <u>www.DynamicEngineers.com</u> Email: <u>Inquiry@DynamicEngineers.com</u> PLL1919BQ-SS-2739MHz-2815MHz-A 2739-2815MHz SMD Phase Locked Loop (PLL) Synthesizer

# **Specifications**

Para	meter	Units	Min.	Typical	Max.
Operating Frequency R	ange	MHz	2739		2815
Output Power		dBm	-2.0	0.0	+2.0
Step Size		KHz		50	
Settling Time		msec		10	30
Output Impedance		Ω		50	
Phase Noise	@1kHz offset	dBc / Hz		-62	-57
Phase Noise	@10kHz offset	dBc / Hz		-91	-86
Phase Noise	@100kHz offset	dBc / Hz		-112	-107
Phase Noise	@1MHz offset	dBc / Hz		-132	-127
2nd Harmonic Suppression		dBc		-40	-20
Sideband Spurious Suppression		dBc			-70
Reference (input frequency)		MHz	5		100
Reference (input level)		dBm	-5		+5
VCO Power Supply (Vcc) Voltage		Vdc		5	
VCO Power Supply (Vcc) Current		mA		15	25
PLL Power Supply (Vcp) Voltage		Vdc		5	
PLL Power Supply (Vcp) Current		mA		5	10
Operating Temperature Range		°C	-40		+85